# NEVABOOST 140 230V 12V

EMF SAFE | 12V | Pb-Ca

## Overview

**NEVABOOST 140 230V 12V**
cod. 807541
Battery charger for charging free electrolyte batteries (WET) with 12 V voltage. Protected against overloads and polarity reversal. Equipped with selector for normal, quick charge/help with starting (BOOST&GO) Equipped with ammeter.

- 1 PH 230V
- CAR
- VAN
- CE MARKING
- EAC CERTIFICATION

## Technical data

- CODE 807541
- MAINS VOLTAGE 230 V - 1 ph 50/60Hz
- CHARGING ABSORBED POWER 230 W
- CHARGING VOLTAGE 12 V
- EFFECTIVE CHARGING CURRENT 20 A
- RATED CHARGE CURR. EN60335-2-29 13 A
- START CURRENT 1V/C EN60335-2-29 50 / 100 (Boost) A
- MIN./MAX RATED REFERENCE CAPACITY 10 / 200 Ah
- ADJUSTMENT POSITIONS 2
- DIMENSIONS 17 - 25 - 16,5 cm
- WEIGHT 5,2 kg
- EAN CODE 800489764143 0
- PIECES/PALLET 95 pz/pallet
- PIECES/PALLET - B 76 pz/pallet - B

## Included Accessories

- CABLE 4 MMQ 1,5 M AND WORK CLAMP - 123987
- CABLE 4MMQ 1,5M + POSITIVE CLAMP - 123988