ENERGY 1500 START 230-400

Overview

ENERGY 1500 START 230-400
cod. 829009
Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage and starting all kinds of cars, vans, light trucks, earth moving equipment, tractors and trucks. Characteristics: choice of normal charge, quick charge (BOOST), quick start * timer for quick charge* remote control * display of charging and starting current * protection against overloads and polarity reversal.

- 3 PH 230V-400V
- REMOTE CONTROLS
- CAR
- BOAT
- TRACTOR
- SMALL VAN
- EXCAVATOR
- VAN
- CE MARKING
- EAC CERTIFICATION

Technical data

- CODE 829009
- MAINS VOLTAGE 230 / 400 V - 3 ph 50/60Hz
- CHARGE/START POWER 7 / 44 kW
- CHARGING VOLTAGE 12 / 24 V
- EFFECTIVE CHARGING CURRENT 150 / 250 A
- RATED CHARGE CURR. EN60335-2-29 130 / 220 A
- START CURRENT 1V/C EN60335-2-29 1000 / 1300 A
- MAX STARTING CURRENT 1700 / 2000 A
- MIN./MAX RATED REFERENCE CAPACITY 70/2000 - 12V Ah
- MIN./MAX RATED REFERENCE CAPACITY 70/4000 - 24V Ah
- ADJUSTMENT POSITIONS 6
- DIMENSIONS 38 - 56 - 88,5 cm

ENERGY 1500 START 230-400

WEIGHT 69 kg

EAN CODE 800489736540 4

PIECES/PALLET 4 pz/pallet

PIECES/PALLET - B 6 pz/pallet - B

Included Accessories

CABLE 0,50MMQ 3M-WORK CLAMP - 713260

CABLE 50MMQ 3M-POSITIVE CLAMP-EYELET Ø10 - 713162

REMOTE CONTROL 6 M - 123993